



ATEO 4

Clevermount™ Design Loudspeaker

► Features

- Patented Clevermount™ mounting system
- Stunning design of loudspeaker and bracket
- Installation & connection in no time
- 1" dome tweeter & 4" Woofer
- 8 Ohm or 100 Volt (4 taps) connection
- High-quality sound reproduction
- Horizontal & vertical mounting
- Available in black and white

► Applications

- Residential applications
- Retail stores
- Clubs
- Pubs
- Restaurants
- ...



The ATEO is a series of extraordinary loudspeakers especially designed for fixed install in indoor applications, ranging from modern residential applications to the most demanding designer applications in environments such as retail stores, pubs, restaurants or even clubs.

The ATEO 4 is the 4" version, with a 1" dome tweeter and a 4" Mid / Low frequency driver, ensuring a true-to-nature, high-fidelity reproduction of music and speech.

It features a stunningly designed and elegant looking ABS housing which is fitted with high-quality components. What makes this loudspeaker range so exceptional is the specially designed mounting bracket using Clevermount™ technology, making the loudspeakers cabinet flow together with the mounting bracket providing a great ease for installing the loudspeaker in one good-looking entity.

The mounting and connection of the loudspeaker is simply done by attaching the included metal wall-plate to the desired location. When mounted, the wires must be connected to the desired terminal of the custom connection block. The desired power tap for 100 Volt or 8 Ohm can be selected by picking the right terminal. After this is done, only five seconds of work is necessary for clipping the loudspeaker onto the wall-plate and tightening the safety screw, then you're ready to rock!

This way, it's really child's play to install a large number of loudspeakers in no-time, even if you are working alone while people are watching what you are doing or installing the speakers up high, standing on a ladder.

All Ateo series speakers are available in Black (/B) or White (/W).

► Specifications

SYSTEM SPECIFICATIONS	
Max power	70 W
RMS power	35 W
Impedance	8 Ohm
Line Transformer Power Taps	24 Watt / 417 Ohm 12 Watt / 833 Ohm 6 Watt / 1667 Ohm 3 Watt / 3333 Ohm
Sensitivity 1W/1m	86 dB
SPL max W / 1m @ 8 Ohm	101 dB
SPL max W / 1m @ 100 V	100 dB
Frequency response (±3dB)	100 Hz - 20 kHz
Frequency range (-10 dB)	65 Hz - 20 kHz
Horizontal dispersion	130°
Vertical dispersion	130°
PRODUCT FEATURES	
Dimensions (Width x Height x Depth)	136 x 244 x 153 mm
Weight net	2.05 Kg
Drivers	1" HF Dome tweeter 4" MF / LF Woofer
Connectors	6-pin custom Terminal Block
Mounting bracket	Clevermount™
Construction	ABS
Front finish	Fine Perforated steel grill
Incline angle	Left & Right 30° Bottom 30° Top 5°
Colour	Black (RAL9005) ATEO4/B White (RAL9010) ATEO4/W
SHIPPING & ORDERING	
Packaging	Carton box (pair)
Shipping weight & volume	5.00 Kg - 0.015 Cbm (2 pcs)
Accessories included	Allen-key wrench
*AUDAC reserves the right to change specifications without notice: this is part of our policy to continually improve our products	

► Architects' and Engineers' Specifications

The loudspeaker shall be a 2-way system, consisting of a 4" woofer and 1" dome tweeter which are housed in a curved ABS housing with a fine perforated steel front grill. The connection and installation of the loudspeaker shall be performed using a Clevermount™ mounting system. The direction of the speaker shall be continuously adjustable in all four directions.

It shall have an RMS power handling of 35 Watt with a maximum power handling of 70 Watt and the frequency response (± 3 dB) shall range from 100 Hz to 20 kHz. The sensitivity shall be 86 dB when measuring with an input signal of 1 Watt at a distance of 1 meter, while the maximum continuous sound pressure level shall be 101 dB.

The loudspeaker shall have an impedance of 8 Ohm and contain a passive built-in crossover network. For use in public address systems, a Multi-Tapping 100 Volt built-in line transformer with power taps for 24 Watt, 12 Watt, 6 Watt and 3 Watt shall be provided. The corresponding power tap shall be selectable by connecting the correct terminal of a special designed 6-pin terminal block connector.

The system's enclosure shall be 244 mm high, 136 mm wide and 153 mm deep and the weight shall not exceed 2.05 Kg.

► Technical drawing

